# A - Module 30



## **Answering Machine Short Manual**

#### Recording and playing back a greeting/information text

A default greeting and a default information message are stored. You can customise the texts.

Example: Text for primary internal number

AM Activation



Press again to record and play back the text for the secondary internal number.

### Switching the answering machine on and off

function key

2 = AB on - greeting text
3 = AM on - information text

Select

Without function key: →®1121 - primary internal number, →®1221 - secondary internal number

### Viewing and listening to messages on your ST 30 AM

1 = AB off

Mail key flashing - new message. Mail key lit steadily - old message already checked



If there is only one call list or message for the answering machine, the "Select" option is not required; the call list or message for the AM is immediately displayed.

#### Functions during playback You can enter commands to control the answering machine during playback. Listen to next message **■** Listen to previous message or repeat current message from beginning Listen to all the messages on the answering machine one after another (A) (C) The playback volume through the loudspeaker can be temporarily adjusted using the arrow keys 1 or 2 "2": Temporary playback at double speed, "1": Normal playback Clear Clear displayed message (Clear Clear all the messages from an answering machine Stop End playback/display OK The external or internal number shown on the display is dialled Recording a memo You can utilise your ST 30 AM as an acoustic notepad, such as to log phone conversations and to record memos or other verbal notes Recording a phone conversation (Logging) AM Memo AM Memo function key function key Internal/external telephone call Start call End recording Handsfree memo recording AM Memo Record memo (handsfree) AM Memo function key function key End recording

Ident no. 1539759 Subject to change without notice. No liability can be accepted for errors contained in this document. Printed in Germany

0041

Internet: http://www.agfeo.de

Recording a memo via the handset

AM Memo

function key

Record memo

AGFEO GmbH & Co. KG Gaswerkstr. 8 D-33647 Bielefeld Technical Hotline: 0190/570122 Mon-Fri: 8:30 a.m. - 5:30 p.m.

\$

(Fri: 2:30 p.m.)

AM Memo

End recording

function key